



CSCI 742 - Compiler Construction

Lecture 23
More Type Rules
Instructor: Hossein Hojjat

March 23, 2018

Recap: Type Judgments and Type Rules

$$\boxed{\Gamma \vdash e : T}$$

If the (free) variables of e have types given by the type environment gamma, then e (correctly) type checks and has type T

$$\boxed{\frac{\Gamma \vdash e_1 : T_1 \quad \dots \quad \Gamma \vdash e_n : T_n}{\Gamma \vdash e : T}}$$

If e_1 type checks in Γ and has type T_1

and ...

and e_n type checks in Γ and has type T_n

then e type checks in Γ and has type T

Type Rules for Block

$$\frac{\overbrace{\Gamma \oplus \{(x_1, T_1), \dots, (x_n, T_n)\}}^{\Gamma_1} \quad \Gamma_1 \vdash s_1 : \text{void} \quad \dots \quad \Gamma_1 \vdash s_n : \text{void}}{\Gamma \vdash \{T_1\ x_1; \dots; T_n\ x_n; s_1; \dots; s_n\} : \text{void}}$$

Type Rules for Block

Empty:

$$\frac{}{\Gamma \vdash \{ \} : \text{void}}$$

Single Statement:

$$\frac{\Gamma \vdash s : \text{void}}{\Gamma \vdash \{s\} : \text{void}}$$

$$\frac{\Gamma \oplus \{(x, T)\} \vdash \{t_2; \dots; t_n\} : \text{void}}{\Gamma \vdash \{T\ x\ ;\ t_2; \dots; t_n\} : \text{void}}$$

declaration is first

$$\frac{\Gamma \vdash s_1 : \text{void} \quad \Gamma \vdash \{t_2; \dots; t_n\} : \text{void}}{\Gamma \vdash \{s_1\ ;\ t_2; \dots; t_n\} : \text{void}}$$

statement is first

Exercise

- Type check the if-expression

```
class World {  
    boolean z;  
    int u;  
    int f(boolean y) {  
        z = y;  
        if (u > 0) {  
            u = u - 1;  
            int z;  
            z = f(!y) + 3;  
            u = z + z;  
        }  
        else {u = 0;}  
        return u  
    }  
}
```

Exercise

```
int fact(int x)  {
    if (x == 0) return 1;
    else return x * fact(x - 1);
}
```

- Prove $\Gamma \vdash x * \text{fact}(x-1) : \text{int}$

where:

$$\Gamma = \{\text{fact} : \text{int} \rightarrow \text{int}, (x : \text{int})\}$$

Mutual Recursion

- Example:

```
int f(int x) {  
    return g(x) + 1;  
}  
  
int g(int x) {  
    return f(x) - 1;  
}
```

- Need environment containing at least

$$f : \text{int} \rightarrow \text{int} \quad \text{and} \quad g : \text{int} \rightarrow \text{int}$$

when checking both f and g

Two-pass approach:

- Scan top level of AST picking up all function signatures and creating an environment binding all global identifiers
- Type-check each function individually using this global environment

Arrays

- Using array as an expression, on the right-hand side

$$\frac{\Gamma \vdash a : T[] \quad \Gamma \vdash i : \text{int}}{\Gamma \vdash a[i] : T}$$

- Assigning to an array

$$\frac{\Gamma \vdash a : T[] \quad \Gamma \vdash i : \text{int} \quad \Gamma \vdash e : T}{\Gamma \vdash (a[i] = e) : \text{void}}$$

Exercise

- Type check the body of function

```
void next(int[] a, int k) {  
    a[k] = a[a[k]];  
}
```

Array Types

- Various kinds of array types in different programming languages

array(T)

- Array with elements of type T and no bounds
- C, Java: `int []`, Modula-3: `array of integer`

array(T, S)

- Array with size, may be indexed $0..size-1$
- C: `int [10]`, Modula-3: `array[10] of integer`

array(T, L, U)

- Array with upper/lower bounds
- Pascal or Ada: `array[2..5] of integer`

array(T, S_1, \dots, S_n)

- Multi-dimensional arrays
- FORTRAN: `real (3, 5)`